

DG-120 DiSEqC H-H Mount

THE SIMPLEST WAY FOR
INSTALLATION AND UPGRADE



SPECIFICATION

Antenna Diameter	120cm Max.
Azimuth Angle	80° East, 160° West
Elevation Angle	25° ~ 75°
Input / Output Voltage	13 / 18 VDC
Power Consumption	50mA (Standby mode) 200mA (Normal) 350mA (Max.)
Rotation Speed	1.9° / sec(at 13V) 2.9° / sec (at 18V)
Satellite Positions	60
Connector	F Type
Command Protocol	DiSEqC1.2
Calibration Function	Yes
Positioning Sensor	Hall Effect Sensor
Manual East / West Buttons	Yes (Build in on the mount for easy installation)
East / West Limit	Fixed Hardware and Programmable Software